

# SHOW CONTROL

## DINA-DR2 LITE

The DINA-DR2 is built on the latest generation of lighting controllers from Nicolaudie Architectural, incorporating all our recent innovations. Designed for DIN rail mounting, the DINA-DR2 is the perfect solution for mid-range lighting installations. It comes with 1024 DMX channels (512 for DINA-DR2 LITE) and can be upgraded to 1536 channels by adding a 3rd DMX universe. Lighting levels, colors, and effects can be programmed from a PC, Mac, Android, iPad, or iPhone using our software available on our website.

<http://www.nicolaudie.com/dina-dr2.htm>



### TECHNICAL DETAILS

<b>Input Power :</b>	12v DC (8-15V range)
<b>Output Procontrol :</b>	DMX512 (x3)
<b>Programmability :</b>	PC / MAC / ANDROID / IOS
<b>Connections :</b>	USB-C Ethernet Screw Terminals for : <ul style="list-style-type: none"><li>• 3 DMX / RDM Universes</li><li>• 8+3 Contact ports</li><li>• 12v power-in</li></ul> Battery holder (CR2032) MicroSD slot
<b>Environment :</b>	IP20 / to 0 to +50°C
<b>Buttons :</b>	Rotary Switch
<b>Dim/Weight :</b>	60x91x62 mm 317g
<b>OS Requirements :</b>	Mac OS X 10.8-10.14 Windows 7/8/10
<b>Standarts :</b>	CE, ETL, Low voltage, EMC, and RoHS
<b>Memory :</b>	SD -Card
<b>Product No :</b>	5150